



UV-Lamps and Accessories Contacts and Lamp Sockets for Low Pressure and Amalgam Lamps



Lamp Socket F4P: plastic type for 4pin lamps

article code	500-001
dimensions (l/w/h)	(16/13/26,4)mm
wire gauge	0,5...0,8mm ²
max. ambient temperature	60°C
max. current	1A
max. voltage	600V

The socket shall be used up to 100W/1A only. Wire must be solid or top coated stranded copper wire. Solder dipped wire ends are not recommended. Strip length: 1,1...1,25cm. Wire leads are to be fully inserted into wiring port. Use wire end ferrules with a length of 12mm. We recommend crimping pliers with square crimping e.g. KNIPEX KN975304.



Lamp Socket KF2P: ceramic type for 2pin lamps

article code	500-009
dimensions (l/w/h)	(14/10/23)mm
wire gauge	0,5...2mm ²
max. ambient temperature	150°C
max. current	6A
max. voltage	600V

Wire must be crimped with included crimp contacts, strip length: 3,5mm. We recommend Crimp Tool KF (500-014) in addition with Insertion Tool KF (500-015) and Extraction Tool KF (500-016).



Lamp Socket KF4P: ceramic type for 4pin lamps

article code	500-002
dimensions (l/w/h)	(17/14/23)mm
wire gauge	0,5...2mm ²
max. ambient temperature	150°C
max. current	6A
max. voltage	600V

Wire must be crimped with included crimp contacts, strip length: 3,5mm. We recommend Crimp Tool KF (500-014) in addition with Insertion Tool KF (500-015) and Extraction Tool KF (500-016).



Lamp Socket KF2G11: ceramic type for 2G11 lamps

article code	500-003
dimensions (l/w/h)	(43/33/23)mm (without spring)
wire gauge	0,5...2mm ²
max. ambient temperature	150°C
max. current	6A
max. voltage	600V

Wire must be crimped with included crimp contacts, strip length: 3,5mm. We recommend Crimp Tool KF (500-014) in addition with Insertion Tool KF (500-015) and Extraction Tool KF (500-016).



C-KF: Crimp Contacts for KF2P, KF4P and KF2G11 Lamp Sockets

article code	500-005
dimensions	inner diameter: 2,26mm, length: 19,8mm
wire gauge	0,5...2mm ²
max. ambient temperature	150°C
max. current	6A
max. voltage	600V

strip length: 3,5mm
We recommend Crimp Tool KF (500-014) in addition with Insertion Tool KF (500-015) and Extraction Tool KF (500-016).

Do not use the sockets in chemical aggressive and/or humid environment!